



# User Manual

## Model #: CT-110A LED DIMMING Controller




### Features:

- 0-100% brightness control, 256 levels;
- On/off function;
- 1 channel can drive up to 15A;
- 0%, 25%, 50%, 75%, 100% brightness pre-saved;
- Pre-saved fade, flashing modes,
- 8 scale speed;

### Specifications:

Vin	12/24VDC
Pout	180W@12VDC; 360W@24VDC
Size	6"x1.6"x1.2" (155*40*30mm)
Weight	3oz.(78g)

### Dimensions:



### Operation Instructions:

**ON/OFF:** Press to turn on or off.

**Mode:** Press to change the mode to next one.

**BRT+ / BRT- :**

**While using Modes M1-M5:**

**+**: Press to increase brightness.

Hold down for continuous brightness increase.

**-**: Press to decrease brightness.


Hold down for continuous brightness decrease.

**Using Modes M6-M7:**

**+**: Press to increase speed of LED mode pattern

**-**: Press to decrease speed of LED mode pattern

### Wiring Instructions:



Note: can access various monochromatic LED modules.

### Remarks:

(1) The input voltage should not exceed 24VDC.

(2) Do not overload; Max. 180W/12V; Max. 360W/24V.

(3) Not for wet installations.

### Modes Chart:

Mode ↕	Mode Description ↕
M1 ↕	0% ↕
M2 ↕	25% ↕
M3 ↕	50% ↕
M4 ↕	75% ↕
M5 ↕	100% ↕
M6 ↕	Flash ↕
M7 ↕	Fade ↕